

## PRV-LX1 – Default Settings

---

---

### OVERVIEW:

The PRV-LX1 recorder ships with default settings for a typical end-user. However, your requirements may differ. The Operating Instructions provide detailed information regarding changing these defaults or reassigning settings according to your preferences. This document lists the PRV-LX1's default settings when shipped from the factory.

To return the PRV-LX1 to the factory default settings, follow the steps below.

- 1) Verify that the unit is in Standby mode.
- 2) Press and hold the STOP button on the recorder's front panel.
- 3) Press and hold the Power button on the front panel.
- 4) Release both buttons simultaneously after the unit powers on.

*Note: Returning the PRV-LX1 to the factory defaults does not erase or remove the imported clips or files.*

**TECHNICAL DETAILS:**

The PRV-LX1 recorder provides default values for the following settings:

Menu	Sub-Menu	Selections	Default Setting
Function (Main)		Drive	HDD
		Project	saves last project chosen by user prior to default reset
		V Input	Composite
		A Input	RCA
Edit – DVD Menu	Target	Menu Edit To	saves last selection chosen by user prior to default reset
	Menu Type/Font	Menu Type	saves last menu selection chosen by user prior to default reset
		Font	saves last font selection chosen by user prior to default reset
	Menu Design	Design Select	saves last menu design selection chosen by user prior to default reset
		Thumbnail	Go To Video
		Button Text	saves last button text selection chosen by user prior to default reset
	Menu Modification	Background	saves last background selection chosen by user prior to default reset
		Image	saves last image selection chosen by user prior to default reset
		Disc Name	saves last disc name chosen by user prior to default reset
		Select Color	saves last select color chosen by user prior to default reset
		Active Color	saves last active color chosen by user prior to default reset
	Navigation Cmd	First Play PGC	saves last first play PGC command chosen by user prior to default reset
		Title Post Cmd	saves last title post command chosen by user prior to default reset
	Del/Init Library	Type	Background
		Design Select	<i>(no default design)</i>

Menu	Sub-Menu	Selections	Default Setting
Edit – Project	Record/Name	Name	saves last edit project name chosen by user prior to default reset
		Protect	saves last selection chosen by user prior to default reset
		Record To	HDD
		Num of Clips	saves last number of recorded/copied clips created in chosen project of HDD prior to default reset
		Num of Titles	saves last number of recorded titles created in chosen project of HDD prior to default reset
	Copy Project	Copy To	(no default location)
	Copy Clip	Source Drive	HDD
		Copy From	saves last name of clip to be copied prior to default reset
		Clip	Beta Input
		Delete	(project prior to factory default reset)
Edit - Title	Target Clip	Edit To (HDD)	Beta Input
	Info/Rename/Del	Name	Beta Input
	Chapter	chapter 1	saves last name of chapter created prior to default reset
	Editing	Trimming Clip	Go To Video
		Chapter Points	Go To Video
	Title	Selection	saves last setting chosen prior to default reset
		SMPTE	saves last setting chosen prior to default reset
Clp00#		saves last setting chosen prior to default reset	
Edit – DVD Disc	Make Disc	Target	DVD1
	Make Image	Target Image	(no default value)
	IN/OUT Point	Preroll Time	5 seconds
		Offset (Frame)	-17 frames
		Record As	Title (Stop)
		IN/OUT Point	00:00:00:00
	Chapter Point	Chapter Point	00:00:00:00
	EDL Command	Command	Finalize
	EDL	No Item	(no default item)
	EDLLOAD/Save/Del	Load	No Item
		Save	Save as ed00.edl

Menu	Sub-Menu	Selections	Default Setting	
APP – Cpy/Imp/Bkup	Disc Copy	Source	DVD1	
		Destination	DVD2	
	Disc Image Copy	Source	DVD1	
		Input Image Name	<i>(no default name)</i>	
	Image Copy/Del	Source Image	THX	
		Destination	DVD1	
	Menu Import	Type	Background	
		Source	Import Directory	
		Source File	ALL	
	EDL Import	Source	Import Directory	
Source File		No Item		
Set Up – System	System Settings	Keyboard	US type (101)	
		Keyboard Repeat Speed	Medium	
		Mouse	Generic	
		Mouse Speed	Medium	
		TimeZone	New York	
		Date(mm/dd/yyyy)	<i>(current date by time zone)</i>	
		Time(hh:mm:ss)	<i>(current time by time zone)</i>	
	F-Key 1-6	F-Key Enable	F-Key Only	
		F1	Not Set	
		F2	Not Set	
		F3	Not Set	
		F4	Not Set	
		F5	Not Set	
		F6	Not Set	
		F-Key 7-12	F7	Not Set
			F8	Not Set
			F9	Not Set
			F10	Not Set
			F11	Not Set
	F12		Not Set	
	Network	Network	OFF	
		DHCP/Manual	DHCP	
	UPS Setting	Model	Disabled	
		Shutdown Delay	30 seconds	
	Information	<i>(all selections)</i>	<i>(no defaults)</i>	
	HDD Tools	Target Drive	HDD	

Menu	Sub-Menu	Selections	Default Setting	
Set Up – Recording	Video/Audio	Video Encode Rate	9.644Mbps	
		Video Filter	OFF	
		Audio Encode	Dolby Digital	
		Audio Level	L + 0 / R + 0	
		Aspect	4:3	
		Setup Level	7.5 IRE	
	Others	Auto Chapter	Manual	
		REC Button	REC Start	
Set Up – Operation	Control Settings	Control	Local	
		Port	RS-422A	
		Time Code	RS-422A	
		Eject Command	Eject	
	Video Settings	External Sync	Disabled	
		OSD	Enabled	
		Composite OUT	Source Monitor	
		Background Color	Black	
			DV OUT	Disabled
			Test Signal	Start
HDD Recording	Time Shift PLAY	Enabled		
GUI Control	Language	English		
Set Up - Playback	Video	Aspect	4:3 (LP)	
		Still Mode	Frame	
	Audio	Dolby Digital OUT	Dolby Digital	
		DTS OUT	OFF	
		96kHz PCM OUT	Convert to 48kHz	
			MPEG OUT	MPEG
	Language	Audio	English	
		Subtitle	English	
		DVD Menu	English	
Others		Parental Level	8	

The information in this document is subject to change without notification.

**ADDITIONAL INFORMATION:**

Additional information is available under the *Business Products Support* area of the Pioneer website:

[http://www.pioneerelectronics.com/pna/business/product/support/home/0,,2076\\_4239,00.html](http://www.pioneerelectronics.com/pna/business/product/support/home/0,,2076_4239,00.html).

For assistance please contact Pioneer Service at (800) 421-1613, your Pioneer representative (sales and technical: [CA] 310-952-2000 or [NJ] 201-327-6400) or refer to the Pioneer corporate website:

[www.pioneerelectronics.com](http://www.pioneerelectronics.com)