



MEP-7000 Firmware Update to Version 2.02

Firmware version 2.02 provides the following improvements:

- Updated with New Feature - Keyword Search by Library Browsing

Firmware Update Procedure:

- 1) Unzip the firmware update file.
*Do **NOT** change the names of the zipped files.*
 - * MEP7KCTL.LDR
 - * MEP7KDRV.LDR
- 2) Copy the files to the root directory of a USB memory device.
USB memory device must be formatted in FAT or FAT32.
- 3) Confirm that the control unit and drive unit are connected.
- 4) Remove any media (CD-R, DVD-R, etc) and USB devices from the unit.
- 5) Turn the power off.
- 6) Press and hold the USB1 STOP and USB2 STOP buttons while powering on the unit.
- 7) Continue holding both buttons until the indicators are flashing red.
- 8) Release both buttons simultaneously.
The message "Connect a USB storage device to the USB port" appears on the display.
- 9) Insert the USB memory device containing the firmware update into the USB2 port.
The firmware update begins as soon as the device is connected to the port. The progress shows as a percentage (%) on the display.

The following message appears when the update is complete:
"Firmware update is completed. Turn the power off and on once before using."
- 10) Turn the power off and remove the USB memory device only after the update is complete.

***Warning: The firmware update takes approximately two (2) minutes.
DO NOT turn the power off during the update procedure.***